

## BEARING TYPE YD - SQUIRREL CAGE MOTORS



شرکت صنایع ماشینهای الکتریکی جوبن (جمنکو)  
Jovain Electrical Machines Industries Co.(JEMCO)

Jovain Electrical Machines Industries Co.(JEMCO)

Type No	Frame Size	Rated Output Kw	Rated Speed RPM	No of Poles	Drive End Bearing	Non Drive End Bearing	AMB.TEMP (°C)	OPER.TIME (h)	GREASE QUANTITY (gr)
YD1161-4A0	160	15	1500	4	6309C3	6309C3	≤25	4000	20
YD1161-2A0		18.5	3000	2			≤40	2000	10
YD1162-2A0		15	3000	2			≤25	2000	20
YD1181-2A0	180	22	3000	2	6311C3	6311C3	≤25	2000	20
YD1181-4A0		18.5	1500	4			≤40	1000	10
YD1182-4A0		22		4			≤25	4000	20
YD1181-6A0		15	1000	6			≤40	2000	10
YD1201-2A0	200	30	3000	2	6312C3	6312C3	≤25	2000	20
YD1202-2A0		37					1000	6	≤40
YD1201-4A0		30	1500	4			≤25	4000	20
YD1201-6A0		18.5	1000	6			≤40	2000	10
YD1202-6A0		22					≤25	2000	20
YD1221-2A0	225	45	3000	2	6313C3	6313C3	≤25	2000	20
YD1221-4A0		37	1500	4			≤40	1000	10
YD1222-4A0		45					≤25	4000	20
YD1221-6A0		30	1000	6			≤40	2000	10
YD1251-2A0	250	55	3000	2	6314C3	6314C3	≤25	2000	20
YD1251-4A0		55	1500	4			≤40	1000	10
YD1251-6A0		37	1000	6			≤25	4000	20
YD1281-2A0	280	75	3000	2	6317C3	6317C3	≤40	2000	10
YD1282-2A0		90					1000	6	≤25
YD1281-4A0		75	1500	4			≤40	1000	10
YD1282-4A0		90					≤25	4000	20
YD1281-6A0		45	1000	6			≤40	2000	10
YD1282-6A0		55					≤25	2000	20

